





ARL-1210UBC-240mcd (3528H236BC)

Features

- PLCC-2 Package.
- Extremely wide viewing angle
- Suitable for all SMT assembly and solder process
- Available on tape and reel
- Moisture sensitivity level: Level 4
- Package:2000pcs/reel
- · RoHS compliant


Description


 The Blue source color devices are made with InGaN on Substrate Light Emitting Diode


Application

- · Optical indicator
- Indoor display
- Automotive lighting
- Backlight f or LCD, switch and Symbol, display
- Tubular light application
- · General use

Package Dimensions












Recommended Soldering Pattern



1. All dimension units are millimeters. 2. All dimension tolerance is ± 0.15 mm

unless otherwise noted.

Part No.	Dice	Lens Type	Luminous i	Viewing	
			Min.	Max.	Angle
ARL-1210UBC-240mcd (3528H236BC)	Blue (InGaN)	Water Clear	160	210	120°

Notes

- 1.01/2 is the angle from optical centerline where the luminous intensity is 1/2 the optical centerline value.
- 2. The above luminous intensity measuremet allowance tolerance $\pm 10\%$.

Electrical / Optical Characteristics at Ta=25°C

Parameter	Symbol	Min.	Тур.	Max	Units	Test Conditions
Forward Voltage	VF	2.8		3.4	V	IF=20mA
Reverse Current	IR			10	uA	VR = 5V
Dominate Wavelength	λd	470	480		nm	IF=20mA

Absolute Maximum Rating at Ta=25°C

Parameter	Symbol	Value	Units
Power dissipation	Pd	105	mW
DC Forward Current	IF	30	mA
Peak Forward Current [1]	IFP	100	mA
Reverse Voltage	VR	5	V
Electrostatic Discharge (HBM)	ESD	1000	V
Operating Temperature	Topr	-40 ~ +85	°C
Storage Temperature	Tstg	-40 ~+100	°C


Note:

1. 1/10 Duty Cycle, 0.1ms Pulse Width.




Typical optical characteristics curves


Ambient Temperature vs. Forward Current




Forward Current VS. Relative Intensity




Forward Voltage VS. Forward Current




Ambient Temperature VS. Relative Intensity



Relative spectral emission



Radiation diagram





Reliability Test Items And Conditions

The reliability of products shall be satisfied with items listed below.

Confidence level:90%

LTPD:10%

Items	Ref.Standard	Test Condition	Test Hours/ Cycles	Sample Size	Ac/ Re
Reflow	JESD22-B106	Temp:260°C max T=10 sec	3 times.	22Pcs.	0/1
Temperature Cycle	JESD22-A104	100°C ±5°C 30 min. 5 min -40°C ±5°C 30 min.	100 Cycles	22Pcs.	0/1
High Temperature Storage	JESD22-A103	Temp:100°C ±5°C	1000Hrs.	22Pcs.	0/1
Low Temperature Storage	JESD22-A119	Temp:-40°C ±5°C	1000Hrs.	22Pcs.	0/1
Life Test	JESD22-A108	Ta=25°C ±5°C IF=20mA	1000Hrs.	22Pcs.	0/1
High Temperature High Humidity Life Test	JESD22-A101	85°C ±5°C / 85%RH IF=5mA	1000Hrs.	22Pcs.	0/1


^{*}The technical information shown in the data sheets are limited to the typical characteristics and circuit examples of the referenced products. It does not constitute the warranting of industrial property nor the granting of any license.

SMT Reflow Soldering Instructions

- 1.Reflow soldering should not be done more than two times
- 2. When soldering , do not put stress on the LEDs during heating

Soldering iron

- 1.When hand soldering, the temperature of the iron must less than 300°C for 3 seconds
- 2. The hand solder should be done only one times




Time

Repairing

3. Repair should not be done after the LEDs have been soldered. When repairing is unavoidable,

a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of LEDs will or will not be damaged by repairing.







Handling Precautions


Compare to epoxy encapsulant that is hard and brittle, silicone is softer and flexible. Although its characteristic significantly reduces thermal stress, it is more prone to damage by external mechanical force.

As a result, Special handling precautions must be observed during assembling using silicone encapsulated LED products, Failure to comply might leads to damage and premature failure of the LED.


1. Handle the component along the side surface by using forceps or appropriate tools; do not directly touch or Handle the silicone lens surface, it may damage the internal circuitry.







2.The outer diameter of the SMD pickup nozzle should not exceed the size of the LED to prevent air leaks. The inner diameter of the nozzle should be as large as possible. A pliable material is suggested for the nozzle tip to avoid scratching or damaging the LED surface during pickup. The dimensions of he component must be accurately programmed in the pick-and-place machine to insure precise pickup and avoid damage during production.



3.Do not stack together assembled PCBs containing LEDs. Impact may scratch the silicone lens or damage the internal circuitry.

4.Not suitable to operate in acidic environment, PH<7.






4. The encapsulated material of the LEDs is silicone. Therefore the LEDs have a soft surface on the top of package. The pressure to the top surface will be influence to the reliability of the LEDs. Precautions should be taken to avoid the strong pressure on the encapsulated part. So when use the picking up nozzle, the pressure on the silicone resin should be proper.

5.LED operating environment and sulfur element composition cannot be over 100PPM in the LED mating usage material.

6.When we need to use external glue for LED application products, please make sure that the external gluematches the LED packaging glue. Additionally ,as most of LED packaging glue is silica gel, and it has strong Oxygen permeability as well as strong moisture permeability; in order to prevent external material from getting into the inside of LED, which may cause the malfunction of LED, the single content of Bromine element is required to be less than 900PPM,the single content of Chlorine element is required to be less than 900PPM,the total content of Bromine element and Chlorine element in the external glue of the application products is required to be less than 1500PPM.




7.Other points for attention, please refer to our LED user manual.




Tape Specifications (Units: mm)

Reel Dimensions



Moisture Resistant Packaging



Note: The tolerances unless mentioned is $\pm 0.1 \text{mm}$, Unit: mm